

Button and Wall Mount Thermal Photocontrols

K4000 Series

These photocontrols install within lighting fixtures, post lamps, or in-wall boxes to provide dusk-to-dawn ON/OFF control of outdoor lighting.

Features

- Mechanical bimetal switch with Cadmium Sulfide photocell
- Compact size fits into standard outlet box, post lamp, wall pack and other lighting fixtures
- Delay feature prevents unwanted OFF switching
- 3/8"-18 NPSM, 3/4" long stem with locking nut and washer gasket

Model #	Style	Voltage	Tungsten	Ballast
K4021C	Button	120 VAC, 50/60 Hz	1800 W	1000 VA
K4023C	Button	208-277 VAC, 50/60 Hz	3100-4150 W	1700-2300 VA
K4027*	Button	347 VAC, 50/60 Hz	5205 W	2880 VA
K4035†	Button	480 VAC, 50/60 Hz	7200 W	4000 VA
K4321C	In-Wall	120 VAC, 50/60 Hz	1800 W	1000 VA


Note: *K4027 is only CSA. †K4035 is not UL/CSA certified

Accessories

Light Shield	6LV1352
Wall Plate Kit	K43-WP-KIT
Lens Stickers (12 pack)	LGLBL



6LV1352



K43-WP-KIT



K4021C



K4321C



Ratings	
Operating Voltage	See Model Table
Inductive Ballast	8.3 A
Incandescent	15 A
Activation On	1 to 5 fc
Activation Off	3 to 15 fc
Operating Temperature	-40° F to 158° F (-40° C to 70° C)
Wire Leads	#18 AWG, 9" L
Dimensions H x W x D	1 13/16" X 1 1/8" X 1 1/8" (46mm x 23.8mm x 20.6mm)
Warranty	2-year limited

Screw-In Lamp Photocontrol

NE1C

This photocontrol screws into a standard light socket to provide quick installation of dusk-to-dawn photocontrol to any lamp fixture.

Features

- For interior or external lights
- ON at dusk, OFF at dawn
- Accommodates any incandescent light up to 150 W
- Not compatible with LED or CFL bulbs



NE1C



Model #	Style
NE1C	Screw-In Lamp

Ratings	
Operating Voltage	120 VAC, 60 Hz
Incandescent	150 W, 120 VAC, 60 Hz
Activation On	1 to 5 fc
Activation Off	3 to 15 fc
Operating Temperature	-40° F to 158° F (-40° C to 70° C)
Warranty	1-year limited