




MC/AC Cable Support Bracket – MCS100



- Neatly isolates, supports and secures MC/AC cables
- Properly spaces MC/AC cable to help eliminate bundling and NEC® & CEC derating issues
- Results in a "neat and workmanlike" installation



| | |
|-----------------------------|-------------------|
| Part Number | MCS100 |
| MC/AC Cable Size | 14-3 to 10-2 |
| Super Neutral Cable Size | 10-2 |
| Material | Steel |
| Finish | Electrogalvanized |
| Cable Capacity | 8 |
| Hole Size 1 (HS1) | 1/4" |
| Hole Size 2 (HS2) | 0.2" |
| Outer Diameter (OD) | 0.43" – 0.56" |
| Certifications | cULus |
| Standard Packaging Quantity | 50 pc |
| UPC | 78285646407 |

NEC is a registered trademark of, and National Electrical Code (NEC) standard is a copyright of the National Fire Protection Association, Inc. UL, UR, cUL, cUR, cULus and cURus are registered certification marks of UL LLC.

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.erico.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

© 2019 nVent All rights reserved

nVent, nVent CADDY, nVent ERICO, nVent ERIFLEX and nVent LENTON are owned by nVent or its global affiliates.

All other trademarks are the property of their respective owners. nVent reserves the right to change specifications without prior notice.

