

# Winter Watchman

## S483 Winter Watchman



Used as a freeze warning device. Completes circuit to household lamp on temperature fall, indicating inoperative heating equipment.

- Plugs directly into wall outlet.
- Lamp plugs into receptacle at bottom of Winter Watchman device.
- Useful when house is unoccupied to notify a neighbor of a temperature drop so heating source fault can be rectified before freeze-up occurs.
- Not precision calibrated for use as a thermostat.

**Dimensions, Approximate:** 3 3/8 in. high x 2 1/8 in. wide x 13/16 in. deep (86 mm high x 54 mm wide x 21mm deep)

**Electrical Ratings:** Load: 120W maximum for incandescent lamp load only.

**Accuracy:** ±5 F (±3 C)

**Ambient Temperature Range:** 30 F to 60 F (-1 C to +16 C)

**Switching Action:** SPST

**Heating:** 1.0A

**Frequency:** 60 Hz

**Sensor Element:** Bimetal

Product Number	Application	Color	Mounting	Setting Temperature Range	
				(F)	(C)
S483B1002	Incandescent Lamp	Beige	Vertical Mount	30 F to 60 F	-1 C to 16 C