

# Specialty Type Switches, Canopy, Pull Chain, Push-Button, Rocker



6PCB11



6FS31



6RS11



6RS11R



6CRB11



6CPB11



6PS11WL



6PSM11



6PSM11NC



6PL

## Features - Specifications

### PULL CHAIN

- Plastic body and nipple
- Nipple 3/8" x 24" x 5/16" (7.9) long
- Aluminum knurled nut, brass or nickel finish
- UL recognized, CSA certified
- NOM

### VARIABLE SPEED PULL CHAIN SWITCH

- Plastic body and nipple
- Brass knurled nut
- Nipple 3/8" x 24" x 3/8" (9.7) long
- UL recognized
- NOM

### CANOPY

- Plastic body
- Steel locknut - brass finish
- Nipple 3/8" - 24" x 3/8" (9.7) long (6CRB11)
- Aluminum nipple, brass finish 3/8" - 27" x 3/32" (7.1) long (6CPB11)
- Brass finish knob and knurled nut

- UL recognized, CSA certified
- NOM

### SNAP-IN ROCKER SWITCH

- Nylon body and rocker
- Polycarbonate rocker (6RS11R)
- Contacts - silver-plated copper-alloy
- .250 (6.4) quick connect tabs
- UL recognized, CSA certified
- NOM

### PUSH-BUTTON SWITCH

- Plastic case
- Nickel-plated brass nipple, knurled nut, hex nut
- Silver-plated brass quick connect terminals (6PSM11NC)
- Nipple 5/16" - 32" x 1/2" (12.7) long
- UL recognized
- CSA certified (6PSM11-6PSM11NC)
- NOM

### SNAP-IN DUAL LENS PILOT LIGHT

- White nylon body
- Polycarbonate lens
- UL recognized, CSA certified
- NOM

## PULL CHAIN SWITCHES WITH WIRE LEADS (For Lamps and Ceiling Fixtures) 6 AMP 125V AC 3 AMP 250V AC 1 AMP 125V

CATALOG NUMBER	SEQUENCE	DESCRIPTION	REMARKS
6PCB11	On-Off	SPST	Brass finish
6PCN11	On-Off	SPST	Nickel finish

## VARIABLE SPEED PULL CHAIN SWITCHES (For Ceiling Fans) 6 AMP 125V AC 3 AMP 250V AC 1 AMP 125V

6FS21	Off-On-On	2 Speed	Quickwire terminals
6FS31	Off-On-On-On	3 Speed	Quickwire terminals

## SNAP-IN ROCKER SWITCHES (For Range Hoods, Appliances) 16 AMP NON IND 125V AC 10 AMP 250V AC

6RS11	On-Off	SPST	Red lighted face
6RS11R	On-Off	SPST	

## ROTARY CANOPY SWITCH (For Lamps and Appliances) 6 AMP 125V AC 3 AMP 250V AC

6CRB11	On-Off	SPST	6" (152.4) wire leads
--------	--------	------	-----------------------

## MAINTAINED CONTACT PUSH-BUTTON CANOPY SWITCH (For Lamps and Appliances) 1 AMP 250V AC 3 AMP 125V AC

6CPB11	On-Off	SPST	6" (152.4) wire leads
--------	--------	------	-----------------------

## MAINTAINED CONTACT PUSH-BUTTON SWITCH (For Lamps and Appliances) 4 AMP 250V 8 AMP 125V 10 AMP 125V AC 3/4 HP 125V AC

6PS11WL	On-Off	SPST	6" (152.4) wire leads
---------	--------	------	-----------------------

## MOMENTARY CONTACT PUSH-BUTTON SWITCH (For Bells and Buzzers) 3 AMP 240V AC 6 AMP 120V AC

6PSM11	Normally Off	SPST	Brass screw terminals
--------	--------------	------	-----------------------

## MOMENTARY CONTACT PUSH-BUTTON SWITCH (For Test & Emergency Equip.) 1 AMP 277V AC 2 AMP 120V AC

6PSM11NC	Normally On	SPST	Brass screw terminals
----------	-------------	------	-----------------------

## SNAP-IN PILOT LIGHT WITH WIRE LEADS (For Panel Indicator Lights)

CATALOG NUMBER	BULB	LENS
6PL	125V Neon	(1) Amber (1) Red

All wire leads are #18 AWG 105° AWM 6" (152.4) long stripped 1/2" (12.7).  
Specifications are subject to change without notice.