

PRESSING

Press Tools



RP 340 Press Tool

The RP 340 is the next generation of pressing technology from RIDGID®. Built to impress.

- 30% smaller tool increases maneuverability*.
- 17% lighter tool reduces operator fatigue*.
- Industry leading 42,000 cycle service interval is 31% longer* to maximize uptime.
- More than 400 presses per charge (with Advanced Lithium 4 Battery).
- Ultimate flexibility with the ability to switch between battery and AC power on the same tool.

*Versus RP 330-B.

Specifications

- Capacity – ½" – 4" (Copper and Stainless Steel), ½" – 2" (PEX).
- 180° Barrel/Jaw Swivel/Hydraulic Ram Output – 7,200 lbs. (32kN).
- Weight – 8.5 lbs/3.8 kg (w/Advanced Lithium 2 Battery), 9.5 lbs/4.3 kg (w/AC Power Adapter).
- Operating Temperature Range – 15°F to 122°F (-10°C to 50°C).
- Approximate Cycle Time – 4 seconds.
- LED-light for continued operations in no or low-light environments.
- Compatible with all Standard Series pressing jaws and attachments from RIDGID®. For use with copper and stainless steel tubing, steel pipe, PEX and cutting soil pipe.
- Battery Tool Kit Includes: RP 340 Press Tool, (2) 18V Advanced Lithium 2 Batteries, 120V Advanced Lithium Battery Charger, and Carrying Case.
- Corded Tool Kit Includes: RP 340 Press Tool, AC power adapter and carrying case

Catalog No.	Description	Weight		Std. Pack
		lb.	kg	
43348	RP 340 Battery Press Tool Kit (No Jaws)	19.0	8.6	1
43353	RP 340 Battery Press Tool Kit w/ProPress Jaws (½"-1")	31.0	14.1	1
43358	RP 340 Battery Press Tool Kit w/ProPress Jaws (½"-2")	51.0	23.1	1
43363	RP 340 Corded Press Tool Kit (No Jaws)	16.0	7.2	1
43368	RP 340 Corded Press Tool Kit w/ProPress Jaws (½"-1")	28.0	12.7	1
43373	RP 340 Corded Press Tool Kit w/ProPress Jaws (½"-2")	48.0	21.8	1
44483	RP 340 Press Tool Only	6.0	2.7	1

Accessories

Catalog No.	Description	Weight		Std. Pack
		lb.	kg	
43378	RP 340 Press Tool Carrying Case	8	3.6	1
44693	18V Advanced Lithium 2.0Ah Battery	1	0.5	1
44698	18V Advanced Lithium 4.0Ah Battery	1½	0.9	1
43458	Advanced Lithium Battery Charger (N. America)	1¼	0.8	1
44798	Charger Replacement Cord (N. America)	¾	0.1	1
44468	120V AC Power Adapter	1	0.5	1
44848	Set of (1) 2.0Ah Battery & (1) 120V Charger, North America	2¼	1.3	1
44853	Set of (2) 2.0Ah Batteries & (1) 120V Charger, North America	3¼	1.7	1